

PANEL GUIDE

Hills Reliance – Dial Capture

Updated March 26, 2025

Latest information<https://www.csl-group.com/panel-guides/hills/hills-reliance-mcm-connection/>

Panel Connection – Dial Capture

Manufacturer	Hills Reliance
Minimum Panel Firmware	1.00
Panel Profile	HILLS-RELIANCE-MCM
Panel Connection	Dial Capture

Panel Connection Information

DualCom Pro 1 – MCM plug-on module – Line A DualCom Pro 2 – DI	PSTN A
DualCom Pro 1 – MCM plug-on module – Line B DualCom Pro 2 – AL	PSTN B

Panel Programming

To access the panel for configuring, press keypad keys *8 then Installer code.

- Keypad will display [Enter the device address then #]
- Then press 0 and # to select the panel.
- Keypad will display [Enter the feature no., then #]

Press 4 then # to select Phone Number One.

- Keypad will display [Feat. 4 Seg# 1].
- Input the telephone number 0123456789 by pressing one digit and the * for each of the numbers in the telephone number then press #
- Keypad will display [Enter the feature no., then #]

Press 5 then # to select System Account Code.

- Keypad will display [Feat. 5 Seg# 1].
- Input the account number by pressing one digit and the * for each of the numbers in the account number then press #
- Keypad will display [Enter the feature no., then #]

Press 6 then # to select Communicator Format.

- Keypad will display [Feat. 6 Seg# 1].
- Input 1 and *
- Keypad will display [Enter the feature no., then #]
- Note: Clear setting value for all other Telephone Number features

Press 12 then # to select Download Access Code

- Keypad will display [Feat. 12 Seg# 1].
- Make a record of or input the download access code that must match what is entered or stored in the DL900 configuration (UDL) program.
- Keypad will display [Enter the feature no., then #]

Press 13 then # to select Number of Rings/Number of Calls to Answer

- Keypad will display [Feat. 13 Seg# 1].
- Input 1 and * then 0 and *
- Keypad will display [Enter the feature no., then #]

Press 14 then # to select Download Control.

- Keypad will display [Feat. 14 Seg# 1].
- Input 1 to 8 so that no numbers are displayed and only '_' are shown. Press #
- Keypad will display [Enter the feature no., then #]