



DUALCOM GRADESHIFT & DIGIAIR UDL PANEL COMPATIBILITY GUIDE

DualCom GradeShift & DigiAir UDL Panel Compatibility

Guide

Panel manufacturers and models that are currently compatible with DualCom GradeShift & DigiAir UDL for alarm reporting using Dial Capture. Panel compatibility is an evolving process with new manufacturers being added regularly. Please call Technical Support for the latest updates on: UK: +44 (0) 1895 474 444 or Ireland: 1800 855 695.

Panel	Model	Connection to Panel	Alarm Signalling Format	RSD
Honeywell Galaxy G3 v5.6 up	48	Dial Capture	Fast Format (FF) / Contact ID (CID) / SIA	Alarm Reporting
Honeywell Galaxy G3 v5.6 up	48, 144, 520	RS485	SIA	Alarm Reporting
Honeywell Dimension v6 up	48, 96, 264, 520	RS485	SIA	Alarm Reporting, UDL and Panel Initiated
Honeywell Dimension v6 up	48, 96, 264, 520	Dial Capture	FF / CID / SIA	Alarm Reporting, UDL and Panel Initiated
Honeywell Flex FX050	E2	RS485	SIA	Alarm Reporting, UDL and Panel Initiated
Honeywell Galaxy G2 v1.52 up	144	Dial Capture (requires external Honeywell digi)	FF / CID / SIA	Alarm Reporting
Honeywell Galaxy	16+	Dial Capture	FF / CID / SIA	Alarm Reporting
Honeywell Galaxy	18,60	RS485	SIA	Alarm Reporting
Castle Caretech/Pyronix	Enforcer	Dial Capture	FF / CID / SIA	Alarm Reporting, UDL and Panel Initiated
Castle Caretech Euro	46, 76	Dial Capture	FF / CID / SIA	Alarm Reporting, UDL and Panel Initiated
Castle Caretech Euro ONE	76	Dial Capture	FF / CID / SIA	Alarm Reporting, UDL and Panel Initiated
Texecom Premier	16, 24, 48, 88, 168	Dial Capture	FF / CID / SIA	Alarm Reporting, UDL and Panel Initiated
Texecom Premier Elite	12, 16, 24, 48, 88, 168, 640	Dial Capture	FF / CID / SIA	Alarm Reporting, UDL and Panel Initiated

(Cooper) Menvier	M800, M1000, M2000	Dial Capture	FF / CID / SIA	Alarm Reporting
(Cooper) Menvier	30, 40, 100, 300	Dial Capture	FF / CID / SIA	Alarm Reporting
(Cooper) Scantronic On wall	9752, 9853, 85EN	Dial Capture	FF / CID / SIA	Alarm Reporting
Cooper i-On	30, 40, 50, 160	Dial Capture	FF / CID / SIA	Alarm Reporting
Risco Prosys	16, 40, 128	Dial Capture	CID / SIA	Alarm Reporting
Risco Eurosec CPX v4.0	CPX	Dial Capture	FF / CID / SIA	Alarm Reporting
Risco Litesys	Litesys 2	Dial Capture	SIA	Alarm Reporting and UDL
Risco Wisdom	Wisdom	Dial Capture	CID / SIA	Alarm Reporting
Risco Agility	Agility 3	Dial Capture	CID / SIA	Alarm Reporting and UDL
Risco GuardTec	480/490/590/593/595/600/601/800	Dial Capture	FF / CID / SIA	Alarm Reporting
Visonic PowerMax	Complete, Pro	Dial Capture	FF / CID / SIA	Alarm Reporting
Visonic PowerMaster	10, 30	Dial Capture	FF / CID	Alarm Reporting
Guardall	PX48i, PX500	Dial Capture	FF / SIA	Alarm Reporting
HKC	1070	Dial Capture	SIA	Alarm Reporting
HKC SecureWatch	16/120	Dial Capture	FF / CID / SIA	Alarm Reporting
HKC Quantum	70	Dial Capture	FF / CID / SIA	Alarm Reporting
InterLogix (Aritech)	Advisor	Dial Capture	CID / SIA	Alarm Reporting
Siemens (Europlex)	SPC6330	Dial Capture	FF / CID / SIA	Alarm Reporting
UTC	ATS1000A-IP, ATS2000A -IP	Dial Capture	CID / SIA	Alarm Reporting
UTC	Aritech CD103, CD1512, CD6103, CD6203, CD7212, CD9103, CD9512, CD14803	Dial Capture	CID / SIA	Alarm Reporting