

PANEL GUIDE

Interlogix Networx – Dial Capture

Updated March 6, 2025

Latest information

<https://www.csl-group.com/panel-guides/carrier/interlogix-networx-dial-capture/>

Panel Connection – Dial Capture

Manufacturer	Carrier – Interlogix
Model	Networx
Cable required?	MCM connected to: - DualCom Pro 1 – MCM plug-on module CS.1.402 - DualCom Pro 2 – DI & AL
Panel Profile	INTERLOGIX-NETWORK-MCM
Panel Bus Connection	Dial Capture

Panel Connection Information

DualCom Pro 1 – MCM plug-on module – Line A DualCom Pro 2 – DI	PSTN Line T
DualCom Pro 1 – MCM plug-on module – Line B DualCom Pro 2 – AL	PSTN Line R

Panel Programming

To access the panel for configuring, press keypad keys *8 then Installer code

- Keypad will display [Enter the device address then #]

- Then press 0 and # to select the panel.
- Keypad will display [Enter the feature no., then #]

Press 4 then # to select Phone Number One

- Keypad will display [Loc# .0 Seg# 1].
- Input the telephone number 0123456789 by pressing one digit and the * for each of the numbers in the telephone number then press #
- Keypad will display [Enter the feature no., then #]

Press 5 then # to select System Account Code

- Keypad will display [Loc# .1 Seg# 1].
- Input the account number by pressing one digit and the * for each of the numbers in the account number then press #
- Keypad will display [Enter the feature no., then #]

Press 6 then # to select Communicator Format

- Keypad will display [Loc# .2 Seg# 1].
- Input 1 and *
- Keypad will display [Enter the feature no., then #]

Note: Clear settingvalue for all other Telephone Number features

Press 12 then # to select Download Access Code

- Keypad will display [Loc. 19 Seg# 1].
- Make a record of or input the download access code that must match what is entered or stored in the DL900 configuration (UDL) program.
- Keypad will display [Enter the feature no., then #]

Press 13 then # to select Number of Rings/Number of Calls to Answer

- Keypad will display [LOC #. 20 Seg# 1].
- Input 1 and * then 0 and *
- Keypad will display [Enter the feature no., then #]

Press 14 then # to select Download Control

- Keypad will display [Loc# .21 Seg# 1].
- Input 1 to 8 so that no numbers are displayed and only ' _ ' are shown. Press #
- Keypad will display [Enter the feature no., then #]