

# Emizon TCD Panel Compatibility



Panel manufacturers and models that are currently compatible with Emizon TCD for alarm reporting using Dial Capture. Panel compatibility is an evolving process with new manufacturers being added regularly. Please call Technical Support for the latest updates on: UK: +44 (0) 1895 474 444 or Ireland: 1800 855 695.

Panel	Model	Connection to Panel	Alarm Signalling Format	RSD
Bosch	Easy Series V2	Dial Capture	Fast Format (FF) / Contact ID (CID) / SIA	Alarm Reporting and UDL
Bosch	Solution 64 16 (AU)	Dial Capture	Fast Format (FF) / Contact ID (CID)	Alarm Reporting and UDL
Castle	Euro	Dial Capture	Fast Format (FF) / Contact ID (CID)	Alarm Reporting and UDL
Cooper / Menvier	Scantronic 95EN, Menvier M series (not T900), ION Range / Menvier 30, 40, 100 & 300	RS232 / Dial capture	Fast Format (FF) / Contact ID (CID)	Alarm Reporting and UDL
GE	ATS 200X/300X/400X, Aritech CD, ATS 200X/300X/400X Dial Capture, ATS Advance Dial Capture	Alarms: RS232, Dial Capture UDL: Dial Capture, RS232	Fast Format (FF) / Contact ID (CID) / SIA	Alarm Reporting and UDL
Guardall	All with RS232 Serial Port	Alarms: RS232, RS485, Dial Capture UDL: Dial Capture or RS232	Contact ID (CID)	Alarm Reporting and UDL
Honeywell	Galaxy G3/Dimension, Galaxy G2, Galaxy (Dial Capture), Galaxy Flex 3 (Dial Capture), Galaxy G500, G512 and Flex 1 & 2, Galaxy Flex 3 RS485	Alarms via RS485 (all panels) Upload download via RS232 (G3) or RS485 (G2/Galaxy (old)/Flex 3)	Fast Format (FF) / Contact ID (CID) / SIA	Alarm Reporting and UDL
DSC	All	Dial Capture	Contact ID (CID) / SIA	Alarm Reporting and UDL

Risco	Prosys	Alarms: Dial Capture UDL: Dial Capture	Fast Format (FF) / Contact ID (CID)	Alarm Reporting and UDL
Risco	Agility Lightsys	Alarms: RS232, RS485, Dial Capture UDL: Dial Capture or RS232	Contact ID (CID) / SIA	Alarm Reporting and UDL
Gardtec	595 Series	Dial Capture	Fast Format (FF) / Contact ID (CID)	Alarm Reporting and UDL
Siemens	SPC Ethernet	Ethernet	Siemens EDP / SIA	Alarm Reporting and UDL
Texecom	Premier / Premier Elite	RS232	Fast Format (FF) / Contact ID (CID) / SIA	Alarm Reporting and UDL
HKC	SecureWave Range	Alarms: RS232, Dial Capture UDL: Dial Capture or RS232	Contact ID (CID) / SIA	Alarm Reporting and UDL
Caddx	Nx,4,8,16 Dial Capture, Via NX585/Serial Interface	Dial Capture or RS232 (when using NX584 automation module)	Contact ID (CID) / SIA	Alarm Reporting and UDL
Paradox	SP/MG (Dial Capture)	Alarms: RS232, Dial Capture UDL: Dial Capture	Contact ID (CID)	Alarm Reporting and UDL
Satel	Integra (Dial Capture)	Alarms: Dial Capture UDL: Dial Capture	SIA	Alarm Reporting and UDL
Satel (SIA over IP)	Integra	Ethernet	SIA	Alarms
NOX (SIA over IP)	-	Alarms: Ethernet	SIA	Alarm Reporting
Kentec Fire	Syncro / Solo	Alarms: RS232 UDL: RS232	SIA	Alarm Reporting and UDL
Orisec	CP range	RS485 (requires CS0461 lead)	Fast Format (FF) / Contact ID (CID) / SIA	Alarm Reporting and UDL